









# TABELLA DI SELEZIONE PRESTAZIONI GEAR UNIT SELECTION TABLES

$P_{1n}$ [kW]	$n_2$ [r/min]	$M_{2n}$ [Nm]	$i$	$f_s$			page			
<b>0.12</b>	30.5	36	45.9	3.3	<b>CHC20</b>	<b>63B5</b>	<b>63A4</b>	<b>16</b>		
	34.9	32	40.1	3.8	<b>(CHC16)</b>					
	39.5	28	35.5	4.3						
	49.1	22	28.5	5.4						
	59.4	18.5	23.6	6.5						
	70.6	15.6	19.8	7.7						
	78.4	14.0	17.9	7.1						
	101	10.8	13.8	9.2						
	118	9.4	11.9	12.8						
	143	7.7	9.8	13.0						
	181	6.1	7.7	13.2						
	246	4.5	5.7	13.4						
	<b>0.18</b>	19.6	84	45.9	1.4	<b>CHC20</b>	<b>71B5/B14</b>		<b>71A6</b>	<b>16</b>
		22.4	74	40.1	1.6	<b>(CHC16)</b>				
25.4		65	35.5	1.8						
31.6		52	28.5	2.3						
30.5		54	45.9	2.2	<b>CHC20</b>	<b>63B5</b>	<b>63B4</b>	<b>16</b>		
34.9		47	40.1	2.5	<b>(CHC16)</b>					
39.5		42	35.5	2.9						
49.1		34	28.5	3.6						
59.4		28	23.6	4.3						
70.6		23	19.8	5.1						
78.4		21	17.9	4.8						
101		16.3	13.8	6.1						
118		14.0	11.9	8.6						
143		11.6	9.8	8.6						
181	9.1	7.7	8.8							
246	6.7	5.7	8.9							
19.4	85	46.5	2.3	<b>CHC25</b>	<b>71B5/B14</b>	<b>71A6</b>	<b>17</b>			
22.2	74	40.6	2.7							
25.1	66	35.9	3.0							
31.2	53	28.9	3.8							
30.1	55	46.5	3.7	<b>CHC25</b>	<b>63B5</b>	<b>63B4</b>	<b>17</b>			
34.5	48	40.6	4.2							
<b>0.25</b>	19.6	117	45.9	1.0	<b>CHC20</b>	<b>71B5/B14</b>	<b>71B6</b>	<b>16</b>		
	22.4	102	40.1	1.2	<b>(CHC16)</b>					
	25.4	90	35.5	1.3						
	31.6	73	28.5	1.7						
	30.5	75	45.9	1.6	<b>CHC20</b>	<b>71B5/B14</b>	<b>71A4</b>		<b>16</b>	
	34.9	66	40.1	1.8	<b>(CHC16)</b>					
	39.5	58	35.5	2.1						
	49.1	47	28.5	2.6						
	59.4	39	23.6	3.1						
	70.6	32	19.8	3.7						



$P_{1n}$ [kW]	$n_2$ [r/min]	$M_{2n}$ [Nm]	$i$	$f_s$			page		
<b>0.25</b>	78.4	29	17.9	3.4	<b>CHC20</b>	<b>71B5/B14</b>	<b>71A4</b>	<b>16</b>	
	101	23	13.8	4.4	<b>(CHC16)</b>				
	118	19.5	11.9	6.2					
	143	16.1	9.8	6.2					
	181	12.6	7.7	6.3					
	246	9.3	5.7	6.4					
	19.4	118	46.5	1.7	<b>CHC25</b>	<b>71B5/B14</b>	<b>71B6</b>	<b>17</b>	
	22.2	103	40.6	1.9					
	25.1	91	35.9	2.2					
	31.2	74	28.9	2.7					
	30.1	76	46.5	2.6	<b>CHC25</b>	<b>71B5/B14</b>	<b>71A4</b>		
	34.5	66	40.6	3.0					
	39.0	59	35.9	3.4					
	48.5	47	28.9	4.2					
	<b>0.37</b>	30.5	111	45.9	1.1	<b>CHC20</b>	<b>71B5/B14</b>	<b>71B4</b>	<b>16</b>
		34.9	97	40.1	1.2	<b>(CHC16)</b>			
		39.5	86	35.5	1.4				
		49.1	69	28.5	1.7				
59.4		57	23.6	2.1					
70.6		48	19.8	2.5					
	78.4	43	17.9	2.3					
	101	33	13.8	3.0					
	118	29	11.9	4.2					
	143	24	9.8	4.2					
	181	19	7.7	4.3					
	246	14	5.7	4.4					
	19.4	175	46.5	1.1	<b>CHC25</b>	<b>80B4/B14</b>	<b>80A6</b>	<b>17</b>	
	22.2	153	40.6	1.3					
	25.1	135	35.9	1.5					
	31.2	109	28.9	1.8					
	30.1	113	46.5	1.8	<b>CHC25</b>	<b>71B5/B14</b>	<b>71B4</b>		
	34.5	98	40.6	2.0					
	39	87	35.9	2.3					
	48.5	70	28.9	2.9					
	58.7	58	23.8	3.5					
	81.9	41	17.1	3.9					
	20.4	167	44.2	1.8	<b>CHC30</b>	<b>80B5/B14</b>	<b>80A6</b>	<b>18</b>	
	26.3	129	34.2	2.3					
29.4	115	30.6	2.6						
<b>0.55</b>	101	50	13.8	2.0	<b>CHC20</b>	<b>80B5/B14</b>	<b>80A4</b>		<b>16</b>
	118	43	11.9	2.8	<b>(CHC16)</b>				
	143	35	9.8	2.8					
	181	28	7.7	2.9					
	246	20	5.7	2.9					

# TABELLA DI SELEZIONE PRESTAZIONI GEAR UNIT SELECTION TABLES

$P_{1n}$ [kW]	$n_2$ [r/min]	$M_{2n}$ [Nm]	$i$	$f_s$			page	
<b>0.55</b>	19.4	260	46.5	0.8	<b>CHC25</b>	<b>80B5/B14</b>	<b>80B6</b>	<b>17</b>
	22.2	227	40.6	0.9				
	25.1	201	35.9	1.0				
	31.2	162	28.9	1.2				
	37.7	134	23.9	1.5				
	30.1	167	46.5	1.2	<b>CHC25</b>	<b>80B5/B14</b>	<b>80A4</b>	<b>17</b>
	34.5	146	40.6	1.4				
	39	129	35.9	1.5				
	48.5	104	28.9	1.9				
	58.7	86	23.9	2.3				
	69.7	72	20.1	2.8				
	81.9	62	17.1	2.6				
	94.5	53	14.8	3.7				
	17.5	287	51.3	1.0	<b>CHC30</b>	<b>80B5/B14</b>	<b>80B6</b>	<b>18</b>
	20.4	248	44.2	1.2				
26.3	192	34.2	1.6					
29.4	171	30.6	1.8					
27.3	185	51.3	1.6	<b>CHC30</b>	<b>80B5/B14</b>	<b>80A4</b>	<b>18</b>	
31.7	159	44.2	1.9					
40.9	123	34.2	2.4					
45.8	110	30.6	2.7					
<b>0.75</b>	101	68	13.8	1.5	<b>CHC20</b>	<b>80B5/B14</b>	<b>80B4</b>	<b>16</b>
	118	58	11.9	2.1	( <b>CHC16</b> )			
	143	48	9.8	2.1				
	181	38	7.7	2.1				
	246	28	5.7	2.1				
	302	23	4.6	2.6				
	30.1	228	46.5	0.9	<b>CHC25</b>	<b>80B5/B14</b>	<b>80B4</b>	<b>17</b>
	34.5	199	40.6	1.0				
	39	176	35.9	1.1				
	48.5	142	28.9	1.4				
	58.7	117	23.9	1.7				
	69.7	99	20.1	2.0				
	81.9	84	17.1	1.9				
	94.5	73	14.8	2.7				
	116.2	59	12.1	3.4				
	141	49	9.9	3.3				
	189	36	7.4	3.3				
	257	27	5.5	3.7				
	20.4	338	44.2	0.9	<b>CHC30</b>	<b>90B5/B14</b>	<b>90S6</b>	<b>18</b>
	26.3	261	34.2	1.1				
	29.4	234	30.6	1.3				
36	191	25.0	1.6					
27.3	252	51.3	1.2	<b>CHC30</b>	<b>80B5/B14</b>	<b>80B4</b>	<b>18</b>	

$P_{1n}$ [kW]	$n_2$ [r/min]	$M_{2n}$ [Nm]	$i$	$f_s$			page		
<b>0.75</b>	31.7	217	44.2	1.4	<b>CHC30</b>	<b>80B5/B14</b>	<b>80B4</b>	<b>18</b>	
	40.9	168	34.2	1.8					
	45.8	150	30.6	2.0					
	56	123	25.0	2.4					
	66.2	104	21.2	2.7					
	76.9	89	18.2	3.1					
	91.5	75	15.3	3.7					
	17.5	392	51.3	1.3	<b>CHC35</b>	<b>90B5/B14</b>	<b>90S6</b>		
	20.4	338	44.2	1.5	<b>CHC40</b>				
	26.3	261	34.2	1.8					
	29.4	234	30.6	2.1					
	27.3	252	51.3	2.0	<b>CHC35</b>	<b>80B5/B14</b>	<b>80B4</b>	<b>19</b>	
	31.7	217	44.2	2.3	<b>CHC40</b>				
	40.9	168	34.2	2.9					
	<b>1.1</b>	101	99	13.8	1.0	<b>CHC20</b>	<b>80B5/B14</b>		<b>80C4</b>
		118	86	11.9	1.4	<b>(CHC16)</b>			
		143	71	9.8	1.4				
		181	56	7.7	1.4				
		246	41	5.7	1.5				
		302	33	4.6	1.8				
	48.5	208	28.9	1.0	<b>CHC25</b>	<b>80B5/B14</b>	<b>80C4</b>		<b>17</b>
	58.7	172	23.9	1.2					
	69.7	145	20.1	1.4	<b>CHC25</b>	<b>90B5/B14</b>	<b>90S4</b>		
	81.9	123	17.1	1.3					
	94.5	107	14.8	1.9					
	116	87	12.1	2.3					
	141	72	9.9	2.2					
	189	53	7.4	2.3					
	257	39	5.5	2.5					
		31.7	318	44.2	0.9	<b>CHC30</b>	<b>90B5/B14</b>	<b>90S4</b>	
40.9		246	34.2	1.2					
45.8		220	30.6	1.4					
56		180	25.0	1.7					
66.2		152	21.2	1.8					
76.9		131	18.2	2.1					
91.5		110	15.3	2.5					
27.3		370	51.3	1.4	<b>CHC35</b>	<b>90B5/B14</b>	<b>90S4</b>		
31.7		318	44.2	1.6	<b>CHC40</b>				
40.9		246	34.2	1.9					
	45.8	220	30.6	2.2					
	56	180	25.0	2.7					
	66.2	152	21.2	2.8					
	76.9	131	18.2	3.2					
	91.5	110	15.3	3.8					

# TABELLA DI SELEZIONE PRESTAZIONI GEAR UNIT SELECTION TABLES

$P_{1n}$ [kW]	$n_2$ [r/min]	$M_{2n}$ [Nm]	$i$	$f_s$			page		
<b>1.5</b>	69.7	197	20.1	1.0	<b>CHC25</b>	<b>90B5/B14</b>	<b>90L4</b>	<b>17</b>	
	81.9	168	17.1	1.0					
	94.5	145	14.8	1.4					
	116	118	12.1	1.7					
	141	98	9.9	1.6					
	189	73	7.4	1.7					
<b>1.5</b>	257	54	5.5	1.9	<b>CHC25</b>	<b>90B5/B14</b>	<b>90L4</b>	<b>17</b>	
	40.9	336	34.2	0.9	<b>CHC30</b>	<b>90B5/B14</b>	<b>90L4</b>	<b>18</b>	
	45.8	300	30.6	1.0					
	56	245	25.0	1.2					
	66.2	208	21.2	1.3					
	76.9	179	18.2	1.6					
	91.5	150	15.3	1.9					
	111	124	12.6	2					
	128	107	10.9	1.7					
	177	78	7.9	2.3					
	255	54	5.5	2.8					
	26.3	523	34.2	0.9	<b>CHC35</b>	<b>100B5/B14</b>	<b>100L6</b>	<b>19</b>	
	29.4	467	30.6	1	<b>CHC40</b>				
	36	382	25	1.3					
<b>1.5</b>	27.3	504	51.3	1.0	<b>CHC35</b>	<b>90B5/B14</b>	<b>90L4</b>	<b>19</b>	
	31.7	434	44.2	1.2	<b>CHC40</b>				
	40.9	336	34.2	1.4					
	45.8	300	30.6	1.6					
	56	245	25.0	2					
	66.2	208	21.2	2					
	76.9	179	18.2	2.3					
	91.5	150	15.3	2.8					
	<b>2.2</b>	76.9	262	18.2	1.1	<b>CHC30</b>	<b>100B5/B14</b>	<b>100LA4</b>	<b>18</b>
		91.5	220	15.3	1.1				
111		182	12.6	1.4					
128		157	10.9	1.1					
177		114	7.9	1.6					
255		79	5.5	1.9					
36		560	25.0	0.9	<b>CHC35</b>	<b>112B5/B14</b>	<b>112M6</b>	<b>19</b>	
42.6		474	21.2	0.9	<b>CHC40</b>				
49.4		408	18.2	1					
40.9		493	34.2	1	<b>CHC35</b>	<b>100B5/B14</b>	<b>100LA4</b>	<b>19</b>	
45.8		440	30.6	1.1	<b>CHC40</b>				
56		360	25.0	1.3					
66.2		305	21.2	1.4					
76.9		262	18.2	1.6					
91.5	220	15.3	1.9						
111	182	12.6	1.9						

